

# Bells

## Fire Bell



## Features

- Low current consumption
- Universally recognisable sound
- Diode polarised
- Choice of gong sizes (6" and 8")
- Approved to EN54 part 3

## Overview

The Klaxon Fire Bell is a motorised bell designed for fire alarm applications. Its low current consumption and universally recognisable alarm sound makes it an ideal choice for many alarm systems.

Designed for ease of installation, it features a robust steel gong.

Units are finished in red and are available in two gong sizes: 6" and 8".


Depending on quantity, labels can be branded with a customer's name and logo.

- Fire
- Railway/Marine
- Security
- Hazardous Area
- Industrial
- Public Warning


## Applications

- Fire alarm; emergency alarm; lift alarm
- Indoor

NOTE: MOUNTING HOLES ARE PROVIDED FOR BESA OR DIRECT WALL MOUNTING



NOTE: ALL MOUNTING HOLE DIMENSIONS FOR THE 8" BELL ARE THE SAME AS THE 6" BELL



Part No.	Gong Size	Colours	Audibility at 1m	Tones	Voltage	Current
18-980851	6"	Red	Up to 95dB (A)	1	19-28V DC	20mA
18-980852	8"	Red	Up to 98dB (A)	1	19-28V DC	20mA

IP Rating: IP21C    Rating: Continuous    Frequency: N/A    Operating Temp: -10°C to +55°C  
 Dome Construction: Steel    Weight: 0.92kg (6") & 1.27kg (8")    Compliance: EN54 3