



EN

Installation Manual

Installation

- Disassemble the gong (2) by unscrewing the hex bolt (1).
- Ensuring that the terminals are at the top of the unit, feed the field wiring through the entry hole (3).
- Connect wiring (max 2.5mm²) to terminals (4), observing polarity.
- Assemble the gong to the base, and fix securely with the hex bolt.

Technical Specification:

Supply Voltage Range.....	19-28V DC
Current	20mA
Peak Sound Level	150mm dome - 95 dBA at 1m
	200mm dome - 98 dBA at 1m
Operating Temperature Range	-10°C to +55°C
Casing	High impact polycarbonate
IP Rating	IP21C



The European directive "Waste Electrical and Electronic Equipment" (WEEE) aims to minimise the impact of electrical and electronic equipment waste on the environment and human health. To conform with this directive, electrical equipment marked with this symbol must not be disposed of in European public disposal systems. European users of electrical equipment must now return end-of-life equipment for disposal. Further information can be found on the following website: <http://www.recyclethis.info/>.

SE

Installationsmanual

Installation

- Montera isär klockan (2) genom att lossa sexkantsbulten (1).
- Kontrollera att kontakterna sitter överst på enheten och mata fältkabeln genom ingångshålet (3).
- Anslut kabelledningen (max 2,5 mm²) till kontakterna (4) och ta hänsyn till polerna.
- Montera klockan på basen och fäst den säkert med sexkantsbulten.

Teknisk specifikation:

Matningsspänningsområde	19-28V DC
Ström	20mA
Toppljudnivå	150mm huv - 95 dBA vid 1m
	200mm huv - 98 dBA vid 1m
Arbetstemperatur	- 10°C to + 55°C
Hus	Hus av extra slagåligt polykarbonat
IP-värde	IP21C



Det europeiska direktivet om avfall som utgörs av eller innehåller elektriska eller elektroniska produkter (WEEE) har i syfte att minimera verknigen av elektriskt och elektroniskt avfall på miljö och människors hälsa. För att följa detta direktiv, får elektrisk utrustning märkt med denna symbol inte avfallshanteras i europeiska kommunala avfallssystem. Europeiska brukare av elektrisk utrustning måste numera lämna tillbaka uttjänad utrustning för avfallshandtering. Ytterligare information finns på följande hemsida: <http://www.recyclethis.info/>.

EN54-3

Fire Alarm Device – Sounder

Type A: Indoor use

18-980851 & 18-980852

Technical Data: Document 18-186839



0832-CPD-0760 (150mm)
0832-CPD-0761 (200mm)